



Get down on it. Get it. And don't let go. This is: The **Big Payback**, your "*main-squeeze.*"

The Big Payback is a 100%-original, 100%-analog VCA feedback-compressor. **Plus**, it doubles as a *Dynamic-Expander*. **And**, an *Auto-Volume-Swell* (like the ol' BOSS® SG-1 Slow Gear).

Oh, and its **REALLY** easy to use, too. By the way, Thank You for supporting Mr. Black and purchasing this pedal. We think you'll really, really like it. Let's not kid ourselves, it sounds great. ☺

Can I get that squish?

- Plug your guitar into the input jack (right side phone jack) and your amp into the output jack (left side phone jack).
- Start with all the knobs set straight up. That's the basic "perfect" starting point. You might not even notice just how good this thing sounds till you turn it off and wonder why it sounds so bunk, off.
- Try turning the Attack knob all the way down and hit your instrument **HARD**. That's that auto-swell. And thickener.
- Turn the Comp. knob fully CCW and the Attack knob fully CW for the special ***Dynamic-Expander*** setting. It's really something special. Get stoked.

Features:

- Highly responsive and transparent dynamic compression and expansion
- From 1:2 up to 40:1 compression ratio
- *Dynamic-Expansion* mode with COMP. control set to minimum (full CCW)
- ~4.4V peak-to-peak max. signal input before onset of clipping (that's A LOT)
- True-bypass
- 9VDC power (2.1mm negative center pin adapter) or internal 9V battery

Like every Mr. Black pedal, this fine piece of kit is designed and 100% handmade in the "south-easy" side of Portland, OR.

Replacing the 9V battery is easier than your prom date after a few champy's. Just grab your trusty phillips head screwdriver and remove the four screws holding the backing plate on. You'll see just what to do; like its prom night all over again. You dirty, dirty, hustler, you.

If you haven't already, join the Black List for news, specials, promos and even the occasional hot dog. Slide over to: www.mrblackpedals.com to sign up. Its free. And free is a good color on me.

Controls:

- **VOLUME:** You already know
 - Full CCW: Mute
 - Full CW: LOUDest
- **ATTACK:** Sets attack rate
 - Full CCW: ~0.5s (hecka slow...)
 - Full CW: ~1mS (*real* fast!)
- **COMP.:** Adjusts compression ratio
 - Full CCW: *Dynamic-Expansion* mode (1:2 – *WHAT?*)
 - Full CW: Approx. 40:1
- **BYPASS SWITCH:** Toggles on/off
 - LED on: **GET ON UP!**
 - LED off: Nah, it ain't cool.

Tech stuff:

- Input impedance: ~470KΩ
- Output impedance: ~2KΩ
- Bypass: True-Bypass
- Current draw: <14mA
- Power requirement: 9VDC adapter or 9V battery