

dark echo special

modulated echo generator

Thank you for supporting Mr. Black and embarking on a journey we started back in 2008: the Dark Echo.

This special edition Dark Echo features a brighter echo with added grit and gristle, and heavier, almost excessive Sway modulation. In fact, at full Sway, it can be downright confusing and nauseating. Ease into this one. It's HEAVY.

Every Mr. Black pedal is designed and handmade in the rainy pacific-northwest; right here in the "south-east" side of Portland, OR.

Kicking things off:

- Turn the lights down low—this isn't the bright echo and you gotta set the mood.
- Plug your guitar into the input jack (right side of the pedal) and your amp into the output jack (left side of the pedal).
- Start with all the knobs set at 9 o'clock. This one is special and them knobs don't need to go all the way up.
- Depress the footswitch and hold onto your lunch.
- You can cop that "oil-can" sound with the Sway *just* past 9:00.
- If you wanna get freaky, start bringing up the Sway control. Slowly.

Features:

- Approx. 30mS – 450mS delay time
- Endless, gnarly echoes which get thicker every time.
- *Extra-heavy* Sway modulation
- True-bypass
- 9VDC power (2.1mm negative center pin adapter) or internal 9V battery

To replace the 9V battery, grab your trusty philips head screwdriver and remove the four screws holding the backing plate on. The battery sits right below the foot-switch. I think you can handle the rest.

If you haven't already, join the Black List for news, specials, promos and even the occasional hot dog.

Visit:

www.mrblackpedals.com to sign up. Its free. And free is a good color on me.

Controls:

- BLEND: Adjusts echo level
Full CCW: No Echo (dry only)
Full CW: Max Echo level
- TIME: Adjusts time between repeats
Full CCW: Shortest time
Full CW: Longest time
- REPEATS: Adjusts echo regeneration
Full CCW: One repeat
Full CW: Runaway/endless
- SWAY: Adjusts Sway modulation
Full CCW: No modulation
Full CW: HEAVY modulation
- BYPASS SWITCH: Toggles on/off
LED on: **ECHO...Echo...echo...**
LED off: Nada.

Tech stuff:

- Input impedance: ~500K Ω
- Output impedance: ~2K Ω
- Bypass: True-Bypass
- Current draw: <30mA
- Power requirement: 9VDC adapter or 9V battery